

## HSA-320/3+1 M

- Surge arresters type T2+T3 ensure the equipotential bonding and reduce switching, induced and residual overvoltage in LV power supply systems.
- The products consist of varistors with big discharge ability.
- Configurations 1+1 and 3+1 are additionally combined with a gas discharge tube which ensures zero leakage current through the PE conductor.
- Installed at the boundaries of LPZ 1 LPZ 3 into subsidiary switchboards and control panels.
- If the product contains two PE (or PEN) terminals, it must not be used as a PE (PEN) bridge.
- **M** indication specifies a type of construction with removable module.
- **S** indication specifies a version with remote monitoring.

| Туре   |                    | HSA-320/3+1 M          |
|--|--------------------|------------------------|
| Test class according to EN 61643-11:2012 (IEC 61643-11:2011)       |                    | T2, T3                 |
| System   |                    | TN-S, TT               |
| Number of poles  |                    | 4                      |
| Rated operating AC voltage   | $U_N$              | 230 V                  |
| Maximum continuous operating voltage AC                            | $U_{C}$            | 320 V                  |
| Maximum discharge current (8/20)                                   | I <sub>max</sub>   | 50 kA                  |
| Nominal discharge current for class II test (8/20)                 | In                 | 20 kA                  |
| Open circuit voltage of the combination wave generator             | U <sub>oc</sub>    | 6 kV                   |
| Total discharge current (8/20) L1+L2+L3+N->PE                      | I <sub>Total</sub> | 50 kA                  |
| Voltage protection level at I <sub>n</sub> (L/N)                   | $U_p$              | < 1.4 kV               |
| Voltage protection level at I <sub>n</sub> (L/PE)                  | $U_p$              | < 1.5 kV               |
| Voltage protection level at I <sub>n</sub> (N/PE)                  | $U_p$              | < 1.4 kV               |
| Voltage protection level at U <sub>oc</sub> (L/N)                  | $U_p$              | < 0.95 kV              |
| Impulse discharge current for class I test (10/350) N/PE           | l <sub>imp</sub>   | 20 kA                  |
| Temporary overvoltage test (TOV) for $t_T = 5 \text{ s (L/N)}$     | U <sub>T</sub>     | 337 V                  |
| Temporary overvoltage test (TOV) for $t_T = 120 \text{ min (L/N)}$ | $U_T$              | 440 V                  |
| Temporary overvoltage test (TOV) for $t_T = 0.2 \text{ s}$ (N/PE)  | $U_T$              | 1 200 V                |
| Response time (L/N)  | t <sub>A</sub>     | < 25 ns                |
| Response time (N/PE)   | t <sub>A</sub>     | < 100 ns               |
| Maximal back-up fuse   |                    | 160 A gL/gG            |
| Residual current   | I <sub>PE</sub>    | ≤ 5 μA                 |
| Short-circuit current rating at maximum back-up fuse               | I <sub>SCCR</sub>  | 60 kA <sub>rms</sub>   |
| Follow current interrupt rating (N/PE)                             | I <sub>fi</sub>    | 0.1 kA <sub>rms</sub>  |
| Lightning protection zone  |                    | LPZ 1-2, LPZ 2-3       |
| Housing material   |                    | Polyamid PA6, UL94 V-0 |
| Degree of protection   |                    | IP20                   |
| Operating temperature  | 9                  | -40 ÷ 70 °C            |
| Humidity range   | RH                 | 5 ÷ 95 %               |
|  |                    |                        |



| Туре  |   | HSA-320/3+1 M   |
|---|---|---|
| Minimum cross-section of connected Cu conductors accord. to HD 60364-5-53:2022 (doesn't apply to $_{\rm s}$ V" connection) for T2 | S | 2.5 mm <sup>2</sup> (L, N)<br>6 mm <sup>2</sup> (PE, PEN) |
| Clamp fastening range (solid conductor)   |   | 1.5 ÷ 25 mm <sup>2</sup>                                  |
| Clamp fastening range (stranded conductor)  |   | $1.5 \div 16 \text{ mm}^2$                                |
| Tightening moment   |   | 3 Nm  |
| Installation  |   | On DIN rail 35 mm   |
| Modular width   |   | 4 TE  |
| Operating position  |   | Any   |
| Product placement environment   |   | Internal  |
| Signalling at the device  |   | Optic   |
| Importance of local signaling   |   | OK – clear target<br>FAULT – red target                   |
| Remote signalling   |   | No  |
| Modular design  |   | Yes   |
| Article number of spare module  |   | 27 192  |
| Lifetime  |   | > 100 000 h   |
| Designed according to standards   |   |   |
| Requirements and test methods for SPDs connected to low-voltage power systems   |   | IEC 61643-11:2011   |
| Safety of Flammability of Plastic Materials   |   | UL 94   |
| Application standards   |   |   |
| Protection against lightning  |   | IEC 62305:2010  |
| Selection and erection of electrical equipment – Switchgear and controlgear   |   | HD 60364-5-53:2022  |
| Selection and application principles for SPDs connected to low-voltage power systems  |   | CLC/TS 61643-12:2009                                      |
| Ordering, packaging and additional data   |   |   |
| Mass  | m | 460 g   |
| Mass (including the packaging)  | m | 488 g   |
| Packaging dimensions (H x W x D)  |   | 74 x 112 x 73 mm  |
| Packaging value   | V | 0.61 dm <sup>3</sup>                                      |
| ETIM group  |   | EG000021  |
| ETIM class  |   | EC000941  |
| Customs tariff no.  |   | 85363010  |
| EAN code  |   | 8590681116487   |
| Art. number   |   | 27 523  |
|   |   |   |




**The link in the QR code** leads to the online presentation of the **HSA-320/3+1 M**. There, in addition to the always up-to-date data sheet, you will also find all diagrams and drawings, declarations of conformity, or 2D or 3D models and other necessary materials. For more information, visit **www.hakel.com** 





## Application wiring diagram (installation)



## Internal diagram

