

HLSA12,5-275 S

- Lightning impulse current and surge arresters type T1+T2+T3.
- The products consist of varistors with big discharge ability.
- HLSA12,5 in configurations 1+1, 3+1 and HLSA12,5G are additionally combined with a gas discharge tube which ensures zero leakage current through the PE conductor.
- Suitable for objects with considerable levels of protection LPL III and LPL IV.
- Installed at the boundaries of LPZ 0 LPZ 1 and higher zones, closest to where overhead line enters the building i.e. in the main distribution boards.
- In case of the installation of a type T1+T2+T3 in the main switchboard, it is also necessary to install type T2 and T3 in any additional distribution boards in the electrical installation.
- If the product contains two PE (or PEN) terminals, it must not be used as a PE (PEN) bridge.
- **M** indication specifies a type of construction with removable module.
- **S** indication specifies a version with remote monitoring.

Туре		HLSA12,5-275 S
Test class according to EN 61643-11:2012 (IEC 61643-11:2011)		T1, T2, T3
System		TN
Number of poles		1
Rated operating AC voltage	U_N	230 V
Maximum continuous operating voltage AC	U _C	275 V
Maximum discharge current (8/20)	I _{max}	50 kA
Impulse discharge current for class I test (10/350)	l _{imp}	12.5 kA
Charge	Q	6.25 As
Specific energy for class I test	W/R	39 kJ/Ω
Nominal discharge current for class II test (8/20)	I _n	25 kA
Open circuit voltage of the combination wave generator	U _{oc}	6 kV
Voltage protection level at I _n	U_p	< 1.2 kV
Temporary overvoltage test (TOV) for $t_T = 5 \text{ s}$	U _T	337 V
Temporary overvoltage test (TOV) for $t_T = 120 \text{ min}$	U_{T}	440 V
Response time	t _A	< 25 ns
Maximal back-up fuse		160 A gL/gG
Residual current	I _{PE}	≤ 700 μA
Short-circuit current rating at maximum back-up fuse	I _{SCCR}	60 kA _{rms}
Lightning protection zone		LPZ 0-1, LPZ 1-2, LPZ 2-3
Housing material		Polyamid PA6, UL94 V-0
Degree of protection		IP20
Operating temperature	θ	-40 ÷ 70 °C
Humidity range	RH	5 ÷ 95 %
Minimum cross-section of connected Cu conductors accord. to HD 60364-5-53:2022 (doesn't apply to "V" connection) for T1	S	6 mm² (L, N) 16 mm² (PE, PEN)
Minimum cross-section of connected Cu conductors accord. to HD 60364-5-53:2022 (doesn't apply to "V" connection) for T2 $$	S	2.5 mm² (L, N) 6 mm² (PE, PEN)

Lightning and surge arresters T1+T2+T3



Туре		HLSA12,5-275 S
Clamp fastening range (solid conductor)		1.5 ÷ 25 mm ²
Clamp fastening range (stranded conductor)		$1.5 \div 16 \text{ mm}^2$
Tightening moment		3 Nm
Installation		On DIN rail 35 mm
Modular width		1 TE
Operating position		Any
Product placement environment		Internal
Signalling at the device		Optic
Importance of local signaling		OK – clear target FAULT – red target
Remote signalling		Yes
Potential free signal contact (S) (recommended cross-section of remote monitoring max. 1 $\mbox{mm}^2\mbox{)}$		AC: 250 V / 1.5 A, DC: 250 V / 0.1 A
Modular design		No
Lifetime		> 100 000 h
Designed according to standards		
Requirements and test methods for SPDs connected to low-voltage power systems		IEC 61643-11:2011
Safety of Flammability of Plastic Materials		UL 94
Application standards		
Protection against lightning		IEC 62305:2010
Selection and erection of electrical equipment – Switchgear and controlgear		HD 60364-5-53:2022
Selection and application principles for SPDs connected to low-voltage power systems		CLC/TS 61643-12:2009
Ordering, packaging and additional data		
Mass	m	135 g
Mass (including the packaging)	m	146 g
Packaging dimensions (H x W x D)		26 x 98 x 73 mm
Packaging value	V	0.19 dm ³
ETIM group		EG000021
ETIM class		EC001457
Customs tariff no.		85363010
EAN code		8590681113196
Art. number		10 007




The link in the QR code leads to the online presentation of the **HLSA12,5-275 S**. There, in addition to the always up-to-date data sheet, you will also find all diagrams and drawings, declarations of conformity, or 2D or 3D models and other necessary materials. For more information, visit **www.hakel.com**





Application wiring diagram (installation)



Internal diagram

